



Dell™ PowerEdge™ 2950 Systems Information Update

This document provides updated information for your system on the following topics:

- Memory mirroring with fully buffered DIMMs
- LCD status messages
- Hard drive carriers
- Linux Enumeration of NICs

Memory Mirroring With Fully Buffered DIMMs

Like the previous generation of memory mirroring technology, mirroring with fully buffered DIMMs (FBDs) provides enhanced protection from memory failure events, enabling a more robust computing environment. The new generation of FBD memory mirroring provides an even higher level of system reliability by providing protection against more complex failures, including multi-bit errors should they ever occur on any pair of FBDs within a mirrored branch.

However, a limitation in the chipset prevents the FBD memory mirroring from recovering from a small set of failures that could occur in specific circumstances. These circumstances include rare Advanced Memory Buffer (AMB) hardware failures or a short in the FBD connector. Although unlikely, this means that FBD memory mirroring cannot assure failover in all circumstances.

LCD Status Messages Update

Table 1 lists updated LCD status messages that can occur and the probable cause for each message. The LCD messages refer to events recorded in the system event log (SEL). For information on the SEL and configuring system management settings, see your systems management software documentation.

Table 1. LCD Status Messages

Code	Text	Causes	Corrective Actions
E1118	CPU Temp Interface	The BMC is unable to determine the CPU(s) temperature status. Consequently, the BMC increases the CPU fan speed to maximum as a precautionary measure.	Turn off the power to the system and restart the system. If the problem persists, see "Getting Help" in your <i>Hardware Owner's Manual</i> .
E122B	0.9 V Over Voltage	0.9 V regulator voltage has exceeded the allowable voltage range.	See "Getting Help" in your <i>Hardware Owner's Manual</i> .



Table 1. LCD Status Messages (continued)

Code	Text	Causes	Corrective Actions
E122C	CPU Power Fault	A voltage regulator failure was detected when the processor regulator(s) was enabled.	See "Getting Help" in your <i>Hardware Owner's Manual</i> .



NOTE: Each diagnostic LCD message is assigned a priority. The highest priority messages will supersede any group of messages with a lower priority.

Hard Drive Carriers

- The SATA interposer board described in "Installing System Components" in the *Hardware Owner's Manual* is not available for the SATAu hard drive carrier for the initial release of this product. SATA hard drives used in your system can only be installed in the SATA hard drive carrier.
- The drive carrier used for SAS drives is labeled "SAS," and is functionally equivalent to the SATAu drive carrier illustrated in the *Hardware Owner's Manual*.

Linux Enumeration of NICs

Linux operating system versions that use the **udev** kernel device manager may enumerate the NICs differently than earlier Linux versions, which used the **devfs** device manager. Although this does not affect system functionality, when using Red Hat® Enterprise Linux (version 4) or SUSE® Linux Enterprise Server 9 operating systems, the NICs may be enumerated backwards: NIC1 may be configured as **eth1** rather than as **eth0**, and NIC2 may be configured as **eth0** rather than as **eth1**. For further information and to find methods of changing default device enumerations, see the **White Papers** section at <http://linux.dell.com>.

Information in this document is subject to change without notice.

© 2006 Dell Inc. All rights reserved. Printed in Brazil.

Reproduction in any manner whatsoever without the written permission of Dell Inc. is strictly forbidden.

Trademarks used in this text: *Dell*, the *DELL* logo, and *PowerEdge* are trademarks of Dell Inc. *Red Hat* is a registered trademark of Red Hat, Inc.; *SUSE* is a registered trademark of Novell Inc. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Dell Inc. disclaims any proprietary interest in trademarks and trade names other than its own.